

Sabre product codes

		Codes	Example
Model			
Sabre 1		SA1	SA2
	Sabre 2	SA2	
	Sabre 3	SA3	
LED quantity			
16 LED*		016	032
	24 LED	024	
	32 LED	032	
	64 LED	064	
Colour temperature			
2700K		27	40
3000K		30	
4000K		40	
Distribution			
Asymmetric - narrow (Diamond+ Optic A1)		A1	F1
Asymmetric - medium (Diamond+ Optic B1)		B1	
Asymmetric - wide (Diamond+ Optic C2)		C2	
Symmetric (Diamond+ Optic C3)		C3	
Wide flood (Diamond+ Optic F1)		F1	
Drive Current			
<p>Drive currents from 300mA to 1000mA are available in 50mA increments Insert drive current value in 4-digit format (eg 750mA = 0750)</p> <p><i>*Sabre 1 available with a maximum drive current of 850mA</i></p>		0300 / 0350 / 0400 / 0450 / 0500 / 0550 / 0600 / 0650 / 0700 / 0750 / 0800 / 0850 / 0900 / 0950 / 1000	0750
Mounting			
Stirrup bracket (standard)		R	R
Ø76mm Post top		PT	
Product colours			
RAL 7046 Mid grey		CF	CF
Control			
No photocell		N	IUC
Photocell 35 lux (1:0.5) (Sabre 2 and 3 only)		U	
Part night switching Photocell 35 lux (1:0.5) (switch off midnight - 05:30) (Elexon regime 762) (Sabre 2 and 3 only)		A4	
Photocell 35 lux (1:0.5) + pre-programmed dimming (dimmed to 50% midnight - 05:30) (Elexon regime 531) (Sabre 2 and 3 only)		D8	
3 pin NEMA (Sabre 2 and 3 only)		E	
5 pin NEMA (Sabre 2 and 3 only)		C3	
7 pin NEMA (Sabre 2 and 3 only)		D2	
4 pin Zhaga socket (Sabre 2 and 3 only)		Z4	
Integral CMS - Urban Control (Sabre 2 & 3 only)		IUC	
Integral CMS - Telensa (Sabre 2 & 3 only)		ITE	
Integral CMS - Mayflower (Sabre 2 & 3 only)		IMA	
<i>Pre-programmed dimming [1]</i>			
Presence detector			
Presence detector (Sabre 2 & 3 only)		PD	
Example code = SA2 032 40 F1 0750 R CF IUC			

[1] Available as standard subject to further information being provided at time of order.



For further help with specifying a product, please [contact us](#)