

Sabre product codes

		Codes	Example
Model			
Sabre 1		SA1	SA2
	Sabre 2	SA2	
	Sabre 3	SA3	
Light Engine			
16 LED*		16	32
	24 LED	24	
	32 LED	32	
	64 LED	64	
Colour Temperature			
2700K		27	40
3000K		30	
4000K		40	
Distribution			
Asymmetric narrow - Diamond+ A Optic		A1	F1
Asymmetric medium - Diamond+ B Optic		B1	
Asymmetric wide - Diamond+ C Optic		C2	
Symmetric - Diamond+ C Optic		C3	
Wide flood - Diamond+ F Optic		F1	
Drive Current			
Drive currents from 300mA to 1000mA are available in 50mA increments Insert drive current value (eg 750mA = 750) <i>*Sabre 1 available with a maximum drive current of 850mA</i>		300 / 350 / 400 / 450 / 500 / 550 / 600 / 650 / 700 / 750 / 800 / 850 / 900 / 950 / 1000	750
Mounting			
Stirrup bracket (standard)		R	R
Ø76mm Post top		PT	
Product Colours			
RAL 7046 Mid grey		CF	CF
Control			
No photocell		N	IUC
Photocell 35 lux (1:0.5) (Sabre 2 and 3 only)		U	
Part night switching Photocell 35 lux (1:0.5) (switch off midnight - 05:30) (Elexon regime 762) (Sabre 2 and 3 only)		A4	
Photocell 35 lux (1:0.5) + pre-programmed dimming (dimmed to 50% midnight - 05:30) (Elexon regime 531) (Sabre 2 and 3 only)		D8	
3 pin NEMA (Sabre 2 and 3 only)		E	
5 pin NEMA (Sabre 2 and 3 only)		C3	
7 pin NEMA (Sabre 2 and 3 only)		D2	
4 pin Zhaga socket (Sabre 2 and 3 only)		Z4	
Integral CMS - Urban Control (Sabre 2 & 3 only)		IUC	
Integral CMS - Telensa (Sabre 2 & 3 only)		ITE	
Integral CMS - Mayflower (Sabre 2 & 3 only)		IMA	
<i>Pre-programmed dimming</i>			
<i>D4i/SR Ready</i>			
Presence Detector			
Presence detector (Sabre 2 & 3 only)		PD	
Example code = SA2 32 40 F1 750 R CF IUC			

For further help with specifying a product, please [contact us](#)