

Waterford product codes

| | | | Codes | Example |
|--|--------------------------|--------------------------|---|---------|
| Family | | | | |
| Waterford | | | WT2 | WT2 |
| Light Engine | | | | |
| Performance LED | | | | |
| 8 LED | | | 8 | 16 |
| 16 LED | | | 16 | |
| 24 LED | | | 24 | |
| Performance CoB | | | | |
| Single CoB | | | PC | |
| | | | Comfort CoB | |
| | | | Single CoB | CC |
| Colour Temperature | | | | |
| 2200K | 2200K | 2200K | 22 | 30 |
| 2700K | 2700K | 2700K | 27 | |
| 3000K | 3000K | 3000K | 30 | |
| 4000K | 4000K | - | 40 | |
| - | Tunable White 1800-4000K | Tunable White 1800-3000K | TW | |
| Distribution | | | | |
| Roads - Diamond+ A Optic | | | A1 / A2 / A3 / A5 / A6 | A1 |
| Pathways - Diamond+ B Optic | | | B1 / B2 / B3 | |
| Areas - Diamond+ C Optic | | | C1 / C2 / C6 | |
| Crossings - Diamond+ Z Optic | | | ZR / ZL / ZF | |
| Roads - AC1 | | | AC1 | |
| Pathways - BC1 | | | BC1 | |
| Areas - CC1 | | | CC1 | |
| Roads - DC1 | | | DC1 | |
| | | | Symmetric | SY |
| Light Shield (optional) | | | | |
| Light shield - internal 150° short (200mm) | | | L1 | - |
| Light shield - internal 150° full | | | L2 | |
| Light shield - internal 180° full | | | L3 | |
| Drive Current | | | | |
| <p>Drive currents from 250mA to 1050mA are available in 50mA increments Insert drive current value (e.g. 700mA = 700)</p> <p>Notes 24 LED = 850mA maximum</p> | | | 250 / 300 / 350 / 400 / 450 / 500 / 550 / 600 / 650 / 700 / 750 / 800 / 850 / 900 / 950 / 1000 / 1050 | 700 |
| Product Colours | | | | |
| RAL 9005 Black | | | 10 | 10 |
| RAL 6005 Light moss green | | | 50 | |
| RAL 3005 Wine red | | | 70 | |
| RAL 5003 Sapphire blue | | | 30 | |
| RAL 7037 Dusty grey | | | 21 | |
| RAL 7016 Anthracite grey | | | 20 | |
| <i>Other colours available on request</i> | | | RAL [specify] | |
| Paint Finish | | | | |
| Polyester powder coat | | | PP | PP |
| Marine-grade coating | | | MG | |
| Control | | | | |
| No control | | | N | 35L |
| Miniature Photocell 20 lux (1:1) | | | 20L | |
| Miniature Photocell 35 lux (1:0.5) | | | 35L | |
| 4-pin Zhaga Book 18 socket (top) | | | Z4 | |
| Integral CMS - Urban Control (AC node with puck antenna) | | | UAC | |
| Integral CMS - Urban Control (DC node with puck antenna) | | | UDC | |
| Integral CMS - Telensa (with monopole antenna) | | | ITE | |
| Integral CMS - Mayflower (with stub antenna) | | | IMA | |
| Internal Wiring | | | | |
| 3-core [default option] | | | 3 | 3 |
| 5-core | | | 5 | |
| Example code = WT2 16 30 A1 700 10 PP 35L 3 | | | | |

For further help specifying a product, please [contact us](#)