

## Kirium Eco product codes

	Codes	Example
<b>Family</b>		
Kirium Eco Mini	KEM	KED
Kirium Eco Midi	KED	
Kirium Eco Max	KEX	
Kirium Eco Ultra	KEU	
<b>Housing Material</b>		
Full die-cast aluminium (upper and lower - available in Mini / Midi / Max / Ultra)	AL	AL
Hybrid (die cast aluminium upper housing housing with UV-stabilised polypropylene lower cover - available in Mini / Midi)	PP	
<b>Colour Temperature</b>		
2200K	22	30
2700K	27	
3000K	30	
4000K	40	
<b>Light Distribution</b>		
Narrow Road Type 1	NR1	NR1
Narrow Road Type 2	NR2	
Medium Road Type 1	MR1	
Medium Road Type 2	MR2	
Wide Road Type 1	WR1	
Wide Road Type 2	WR2	
Traffic Routes	TR	
Asymmetric Area	AA	
Symmetric Area	SA	
Zebra Crossing	PX	
<b>Drive Current</b>		
Drive currents from 250mA to 1050mA are available in 50mA increments Insert drive current value in 4-digit format (eg 250mA = 0250)	0250 / 0300 / 0350 / 0400 / 0450 / 0500 / 0550 / 0600 / 0650 / 0700 / 0750 / 0800 / 0850 / 0900 / 0950 / 1000 / 1050	0750
<b>Electrical Class</b>		
Class I (default)	I	I
Class II	II	
<b>Product Colours</b>		
RAL 7046 Mid Grey	CF	CF
RAL 7035 Light Grey	29	
RAL 9005 Black	10	
<b>Pre-Programmed Dimming (optional)</b>		
Pre-programmed dimming profile (please specify on order)	DIM	-
<b>Integrated Control (optional)</b>		
Miniature Photocell 20 lux (1:1)	U20	U35
Miniature Photocell 35 lux (1:0.5)	U35	
Miniature Photocell 70 lux (1:0.5)	U70	
Integral CMS - Urban Control (with puck antenna)	IUC	
Integral CMS - Telensa (with monopole antenna)	ITE	
Integral CMS - Mayflower (with stub antenna)	IMA	
<b>External Connectivity - Top (optional)</b>		
3-pin NEMA socket	E	-
5-pin NEMA socket	C3	
7-pin NEMA socket	D2	
4-pin Zhaga Book 18 socket	Z4	
<b>External Connectivity - Bottom (optional)</b>		
4-pin Zhaga Book 18 socket (available when fitted with a NEMA or Zhaga Book 18 socket to the top and in full die-cast housings only)	Z4B	-
<b>Example code = KED AL 30 NR1 0750 I CF U35</b>		

For further help with specifying a product, please [contact us](#)