

Katana product codes

| | | | Codes | Example |
|---|----------|-------------|--|---------|
| Family | | | | |
| Katana | | | KAT | KAT |
| Model | | | | |
| Urban | | | U | U |
| Industrial | | | I | |
| Mounting | | | | |
| Wall | | | WW | PT |
| | Post top | | PT | |
| | | Direct post | DP | |
| Module quantity | | | | |
| 1 | 1 | 1 | 1 | 2 |
| 2 | 2 | 2 | 2 | |
| | | 3 | 3 | |
| | 4 | | 4 | |
| Colour temperature | | | | |
| 2700K | | | 27 | 30 |
| 3000K | | | 30 | |
| 4000K | | | 40 | |
| Distribution^[1] | | | | |
| Diamond+ A Optic - Wide road (A1 / A2 / A3 / A4 / A5) | | | A1 / A2 / A3 / A4 / A5 | A1 |
| Diamond+ B Optic - Narrow road (B1 / B2 / B3 / B4 / B5) | | | B1 / B2 / B3 / B4 / B5 | |
| Diamond+ C Optic - Area (C1 / C2 / C3 / C4 / C5) | | | C1 / C2 / C3 / C4 / C5 | |
| Diamond+ D Optic - Standard road (D1 / D2 / D3 / D4 / D5) | | | D1 / D2 / D3 / D4 / D5 | |
| Diamond+ F1 Optic - Floodlighting (F1) | | | F1 | |
| Drive current | | | | |
| Drive currents from 200mA to 1000mA are available in 50mA increments. Insert drive current value in 4-digit format (eg 250mA = 0250) | | | 0200 / 0250 / 0300 / 0350 / 0400 / 0450 / 0500 / 0550 / 0600 / 0650 / 0700 / 0750 / 0800 / 0850 / 0900 / 0950 / 1000 | 0700 |
| Product colours | | | | |
| RAL 7046 Mid grey | | | CF | CF |
| RAL 7035 Light grey | | | 29 | |
| RAL 9005 Black | | | 10 | |
| Control | | | | |
| No photocell | | | N | D2 |
| Photocell 35 lux (1:0.5) | | | U | |
| Part night switching Photocell 35 lux (1:0.5) (switch off midnight - 05:30) (Elexon regime 762) | | | A4 | |
| Photocell 35 lux (1:0.5) + pre-programmed dimming (dimmed to 50% midnight - 05:30) (Elexon regime 531) | | | D8 | |
| 3 pin NEMA | | | E | |
| 5 pin NEMA | | | C3 | |
| 7 pin NEMA | | | D2 | |
| <i>Pre-programmed dimming^[2]</i> | | | | |
| <i>CMS compatible^[2]</i> | | | | |
| <i>SR Ready^[2]</i> | | | | |
| Example code = KAT U PT 2 30 A1 0700 CF D2 | | | | |

[1] For further information on Diamond+ visit dwwindsor.com/diamond

[2] Available as standard subject to further information being provided at time of order.

For further help with specifying a product, please [contact us](#)